

AMENDMENT TO THE CLAIMS

1. (Currently Amended) A method of identifying an estimate for a noise-reduced value representing a portion of a noise-reduced speech signal, the method comprising:

decomposing a portion of a noisy speech signal into a harmonic component and a random component;

determining a scaling parameter for at least the harmonic component;

multiplying the harmonic component by the scaling parameter for the harmonic component to form a scaled harmonic component;

multiplying the random component by a scaling parameter for the random component to form a scaled random component; and

summing the scaled harmonic component and the scaled random component to form the noise-reduced value representing a portion of a noise-reduced speech signal wherein the portion of the noise-reduced speech signal has reduced noise relative to the portion of the noisy speech signal.

2. (Currently Amended) The method of claim 1 wherein decomposing thea portion of thea noisy speech signal comprises modeling the harmonic component as a sum of harmonic sinusoids.

3. (Currently Amended) The method of claim 2 wherein decomposing thea portion of thea noisy speech signal further comprises determining a least-squares solution to identify the harmonic component.

4. (Currently Amended) The method of claim 1 wherein determining a scaling parameter for the harmonic component comprises determining a ratio of anthe energy of the harmonic component to anthe energy of the noisy speech signal.

5. (Original) The method of claim 4 wherein determining a ratio comprises:
summing the energy of samples of the harmonic component;
summing the energy of samples of the noisy speech signal; and
dividing the sum for the harmonic component by the sum for the noisy speech
signal.
6. (Currently Amended) The method of claim 1 wherein decomposing thea portion of thea noisy speech signal comprises decomposing a vector of time samples from a frame of the noisy speech signal into a harmonic component vector of time samples and a random component vector of time samples.
7. (Original) The method of claim 6 further comprising determining a Mel spectrum for the harmonic component from the harmonic component vector of time samples.
8. (Currently Amended) The method of claim 7 wherein multiplying the harmonic component by thea scaling parameter comprises multiplying the Mel spectrum for the harmonic component by the scaling parameterfactor.
9. (Original) The method of claim 8 further comprising forming a Mel Frequency Cepstral Coefficients feature vector from the noise-reduced value.
10. (Currently Amended) The method of claim 9 further comprising using the Mel Frequency Cepstral Coefficients~~Coefficients~~ feature vector to perform speech recognition.
11. (Original) The method of claim 1 further comprising using the noise-reduced value to perform speech recognition.

12. (Original) The method of claim 1 further comprising using the noise-reduced value in speech coding.

13. (Currently Amended) A computer-readable medium having computer-executable instructions for performing steps comprising:

identifying a harmonic component and a random component in a noisy speech signal;

combining the harmonic component and the random component to produce a noise-reduced value representing a noise-reduced speech signal that has reduced noise compared to the noisy speech signal; and

using the noise-reduced value to perform speech recognition.

14. (Currently Amended) The computer-readable medium of claim 13 wherein identifying the harmonic component comprises modeling the harmonic component as a sum of harmonic sinusoids.

15. (Currently Amended) The computer-readable medium of claim 14 wherein identifying the harmonic component further comprises identifying a least-squares solution.

16. (Currently Amended) The computer-readable medium of claim 13 wherein identifying the harmonic component comprises identifying a vector of time samples representing a harmonic component.

17. (Currently Amended) The computer-readable medium of claim 16 wherein identifying the harmonic component further comprises converting the vector of time samples into a Mel spectrum for the harmonic component.

18. (Original) The computer-readable medium of claim 13 wherein combining the harmonic component and the random component comprises forming a sum with the harmonic component and the random component.

19. (Original) The computer-readable medium of claim 18 wherein the sum is a weighted sum formed in part by multiplying the harmonic component by a scaling value for the harmonic component.

20. (Currently Amended) The computer-readable medium of claim 19 further comprising determining the scaling value for the harmonic component by determining a ratio of anthe energy of the harmonic component to anthe energy of the noisy speech signal.

21. (Original) The computer-readable medium of claim 20 wherein the scaling value for the harmonic component is separately determined for each frame of the noisy speech signal.

22. (Original) The computer-readable medium of claim 21 wherein the weighted sum is further determined by multiplying the random component by a scaling value for the random component.

23. (Original) The computer-readable medium of claim 22 wherein the scaling value for the random component is fixed for each frame of the noisy speech signal.

24. (Original) The computer-readable medium of claim 13 wherein using the noise-reduced value to perform speech recognition comprises converting the noise-reduced value into a feature vector and using the feature vector as input to a speech recognition system.

25. (Original) The computer-readable medium of claim 24 wherein the feature vector comprises a Mel Frequency Cepstral Coefficient feature vector.